

## Data Sheet Series 3

### DC313SFB

## Wireless portable doorbell with volume control and two push buttons – White

Simple, reliable and hassle-free, the Honeywell Home DC313SFB front and back door kit comes with adjustable volume to suit your mood, and a LED strobe for added visual alerts. Place one push at your front and back door so you'll never miss a visitor again.



### Pack Contents:

1 x Wireless Portable Doorbell, 2 x Wireless Push Button, 2 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

### Key Features and Benefits:

**Front and Back Door Kit** This front and back door kit provides a simple, hassle-free solution for your home. It comes with two pushes that are pre-linked to one doorbell. Simply place one push at each door so you'll never miss a visitor again.

**Never miss a visitor or delivery** Take your portable doorbell anywhere around your home and garden, with Honeywell ActivLink™ technology providing a reliable wireless range of up to 150m, while the maximum volume of 84dB can be heard up to 80m away.

**Disturbance Free** - Easily adjust the volume to suit your family and mood, or when you simply want some quiet time.

**Visual Alerts** - The LED Strobe provides a discreet but effective visual alert which complements your chosen melody in loud environments, or helps to alert you when the doorbell can't be heard.

**Revolutionary design** - Compact and beautifully designed in a harmonising palette of white and grey, our doorbells are designed with your home in mind.

**Peace of mind** - Peace of mind for visitors, thanks to a LED confidence light on the push button, and peace of mind for you, thanks to the Secret Knock function which plays a different melody, so you know if it's a family member or friend at the door. For total peace of mind, let Honeywell ActivLink™ interconnect your doorbell with Honeywell security accessories and Home Alarm Kits to build your own bespoke home alert and alarm system.

**Reliability and Quality** - Honeywell ActivLink®, using the 868MHz frequency, is our innovative wireless protocol which delivers greater range capability, extended battery life of up to 2 years, and improved connection reliability, all supported by our 2 year product quality guarantee.

## Specification:

### Wireless Portable Doorbell

Colour	White
Wall mounted	Optional
Frequency / Transmission Power / Wireless Range*	868MHz / 150m
Audible Range (Volume)	80m (84dB)
Melodies	6
Sound	Volume Control / Internal Siren
Alarm Time (minutes)	2 (Internal Siren Mode)
Visual Alerts	LED Indicator / LED Strobe
Power	Battery: 4 x LR6 (AA) 1.5V - (not included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Maximum Device Capacity	4 x Wireless Push Button/Wireless Motion Sensor/Wireless Door and Window Sensor
Factory Reset	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	110 (h) x 70 (w) x 42.5 (d) / 169 (g)
Fixings	Brackets / Rawl Plugs / Screws

### Wireless Push Button ( x 2 )

Colour	White
Wall mounted	Optional
Screwless mounting option (Sticky pads)	Yes
Frequency / Transmission Power / Wireless Range*	868MHz / 200m
Visual Alerts	Confidence Light
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Push Button Design	Offset Landscape
Push Name Plate	Yes
IP Rating	IP55
Operating Temperature/Storage Temperature	-20°C to +50°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	30 (h) x 70 (w) x 16 (d) / 23.5 (g)
Fixings	Brackets / Screws / Sticky Pads

### Pack

EAN Code	5004100965110
Pack Dimensions (mm) / Weight (g)	216 (h) x 150 (w) x 68 (d) / 440 (g)
Standard Pack Quantity	4

\* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.

