Honeywell Home

Data Sheet DCP311G

Wireless push button with LED confidence light? Portrait, Grey

The Honeywell Home DCP311G wireless push button combines great functionality with a best in class design. It comes with a LED confidence light which indicates that the push is working, and the Secret Knock function plays a different melody, so you know it's a family member or friend at the door.









Pack Contents:

1 x Wireless Push Button,1 x CR2032 (3V) Battery,1 x Quick Start Guide, 1 x Safety & Guarantee,1 x Declaration of Conformity,

Key Features and Benefits:

Peace of mind - Peace of mind for visitors, thanks to a LED confidence light on the push button, and peace of mind for you, thanks to the Secret Knock function which plays a different melody, so you know if it's a family member or friend at the door. For total peace of mind, let Honeywell ActivLink? interconnect your doorbell with Honeywell security accessories and Home Alarm Kits to build your own bespoke home alert and alarm system.

Specification:

Wireless Push Button	
Colour	Grey
Wall mounted	Optional
Screwless mounting option (Sticky pads)	Yes
Frequency / Transmission Power / Wireless Range*	868MHz/200m
Visual Alerts	Confidence Light
Power	Battery: 1 x CR2032 (3V) - /(included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator/Easy Open Battery Compartment
Push Button Design	Portrait
Push Name Plate	No
IP Rating	IP55
Operating Temperature/Storage Temperature	
Dimensions (mm) / Weight (g)	30 (h) x 70 (w) x 16 (d) / 23.5 (g)
Fixings	Brackets/Rawl Plugs/Screws/Sticky Pads

Pack	
EAN Code / Standard Pack EAN Code	5004100965745 / 5004100967329
Pack Dimensions (mm) / Weight (g)	83 (h) x 146 (w) x 30 (d) / 108 (g)
Standard Pack Quantity	6

^{*} Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.

©2020 Resideo Technologies, I	nc. The Honeywell Home to	rademark is used under lice	ense from Honeywell Interna	ational Inc.