

Data Sheet HS3MAG1S

Wireless door and window sensor - White

Enjoy added peace of mind with the HS3MAG1S Wireless door and window sensor. Link the sensor with your existing Honeywell Home doorbell or home alarm kit, and get alerts whenever a door or window has been left open, or when someone enters or leaves your home.

**Both HS3MAG1S and HS3MAG1N are identical and interchangeable, the only difference are the other European languages on the packaging.,*



Pack Contents:

1 x Wireless Door and Window Sensor, 1 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

Key Features and Benefits:

Door Entry Alerts For added peace of mind, get alerts whenever someone opens a door or window. The wireless door and window sensor, enabled by Honeywell ActivLink™, connects with your Honeywell doorbell or home alarm system to trigger an alert sound.

Specification:

Wireless Door and Window Sensor	
Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Transmission Power / Wireless Range*	868.00 to 868.60MHz / 4.92dBm ERP / 200m
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	71 (h) x 40 (w) x 14 (d) / 28 (g)
Fixings	Screws / Sticky Pads

Pack	
EAN Code / Standard Pack EAN Code	5004100966049 / 5004100966209
Pack Dimensions (mm) / Weight (g)	137 (h) x 146 (w) x 30 (d) / 84 (g)
Standard Pack Quantity	6

* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.

livesell.honeywell.com | ©2015 - 2019 Honeywell International Inc.