

### SPRS8EZZ - Wireless Contactless Tag Reader with built-in siren and 2 Tags



#### KEY FEATURES AND BENEFITS

- Honeywell unique patented bi-directional secure 868 MHz Wireless Technology - longer range (1000m) and improved battery performance.
- Easy installation. Simple to use.
- Up to 10 users / 10 proximity tags.
- Two buttons
- Four LEDs for status

#### PRODUCT SPECIFICATION

Languages covered –  
GB, DE, FR, NL, ES, PT, IT = English, German, French, Dutch, Spanish, Portuguese, Italian

- Colour - White
- Frequency - 868MHz
- Wall Mounting
- 4 years battery life

#### KIT CONTENTS

- 1 x Wireless Contactless Tag Reader fitted with batteries and isolation tab
- 2 x Contactless tags
- 1 x Quick start installation guide
- 1 x Safety and guarantee guide
- 1 x Declaration of conformity
- 1 x Sticky pad

#### INSTALLATION

- Wall mount

#### MECHANICAL & ENVIRONMENTAL

Temperature:	
Operating:	-10°C to +55°C
Dimensions:	110 x 110 x 30mm (HxWxD)
Product Weight:	258g (include battery)

#### POWER SUPPLY

3 x CR123A 3V batteries

#### PERFORMANCE

Siren / Sounder	: 78 dBA at 1m Typical, 74 dBA at 1m Min
-----------------	---

#### Alarm Interface:

RF operating frequency:	868MHz
RF range:	1000m (Open field)

#### PACKAGING DATA

##### SINGLE PRODUCT

EAN code:	5004100969491
Weight:	approx. 300g
Pack dimension:	215 x 150 x 40mm

##### STANDARD PACK

Quantity:	4
-----------	---